



RX4 Serial Receiver

The *Scope™ RX4 Serial Receiver* is designed to give the user add flexibility. The RX4 receiver can receive pages and output the results to a printer or PC for record keeping. The RX4 receiver can activate other devices by means of contact closure. The RX4 can be equipped with firmware to allow the unit to function with a Xlite transmitter in a repeater configuration.

The RX4 Receiver can be configured to respond to all pager addresses or only specified addresses. Output relays can be set for latching or monetary.



Serial output POCSAG receiver

Alphanumeric 1200 baud

Cap code range selectable

Unique and Group ID

Data only function

12 Volts DC

RX4 Serial Receiver

SPECIFICATION SHEET

Operating	11 – 14 Volts DC
Input Voltage	115 Volts AC Wall Adapter UL Approved
Operating Current	50mA
Frequency	457.550, 457.525, 457.575 Mhz
Paging Format	POCSAG
RF Baud Rate	1200 or 512
Type Accepted	FCC Part 15
Size	7 ½ "H x 5 ¼ "W x 1 ½ "D
Weight	1¼ Lbs without AC power Adapter
Antenna	¼ Wave with BNC termination
Serial Port	25-Pin Male "D"