



Bed (SLBECS) Bath (SLBACS)



The wall mounted Bed/Bath Call Station provides residents an assist call and caregivers with Staff Assist functionality. Activating the Bed or Bath station using the **Call Cord, Pull Cord** or pushing the **Help** button will summon a caregiver. Calls can be assigned to display on LED Sign, Computer Monitors or Pager. A **Cancel** button clears active call(s) from the station. You will always know when a call is active by watching for the **LED** to flash. If Staff need Additional assistance simple press the hidden **Assist** button to summon extra support.

Key Features

- ▶ Sealed, easy-to-clean station face
- ▶ Bright Call Status LED
- ▶ Easy battery replacement
- ▶ Communication Wireless
- ▶ Hidden Staff Assist feature
- ▶ Compact low-profile design with easy-view tilted face
- ▶ Water resistant
- ▶ 3 Zone trigger

Specifications

- ▶ Molded using flame-retardant PC/ABS plastic
- ▶ Station weight 6.4 ounces with battery.
- ▶ Station 5.48”W x 1.25”D x 3.65”H

Technical

- ▶ Internal Battery – 3.0V
Type CR123A, Lithium, 1550mAh.
Operating life typical 2 years
- ▶ Current - <50mA @ 10mW transmit
- ▶ Frequency – 433 – 470 Mhz
- ▶ Channel Spacing 12.5 Khz @ 2.5 Khz deviation
- ▶ FCC ID:JRNUSAWAVETRACK

3900 Woodlake Blvd. – Suite 208 – Greenacres, Florida 33463

Tel:561.969.6976 Fax: 561.969.7134